

User Manual



Introduction

The latest style desktop wireless telecommunication products. It can send wireless SMS and voice at anytime, anywhere, suitable remote countries or mountains.

Please take care below instructions before using this phone:

- Please charge the battery continuous more than 12 hours for first time using;
- Do not clean the phone while in operation. Before attempting to clean the Phone, turn the Phone off, disconnect the external power adapter and take out the battery or disconnect the external power supply if used. Before moving the Phone, disconnect the external power adapter or power supply in use. Use a Damp cloth for cleaning. Do not use liquid or aerosol cleaners;
- Do not hold the antenna. This may affect call quality and cause telephone to operate at unintended power levels;
- Keep the antenna free from obstructions and position the antenna straight up. This will ensure best call quality;
- Do not use a damaged antenna. Have this replaced through a qualified technician. Use only antenna approved by the manufacturer. Unapproved antenna may impair the call quality as well as cause damage to the phone;
- Only use the battery and the power adapter or the Power Supply provided with the Instrument. The instrument might get damaged if any other accessories are used. This will also void the warranty;
- It is highly recommended to charge the battery before initial use. The battery might have been discharged during storage and delivery;
- Do not use with car battery. It may lead to electric shock or breakdown.
- Do not throw battery. Batteries are not to be disposed-off by putting them in fire. It may explode or catch fire;
- Do not attempt to change the security codes or components. User is responsible for any consequences arising out of such attempt;

GSM Fixed Wireless Phone (Model: ALB-938GSM)

- Avoid Shock or Impact. Rough handling can cause damage to the body as well as internal circuits;
- Do not paint;
- During lightening, do not touch power plug or phone line. This can cause electric shock or death. Do not touch the external antenna;
- Your phone is to work with 100-240 V AC. Check the voltage before connecting;
- Do not plug many power cords in the outlet;
- Do not touch the plug with wet hands. Always grasp and pull the plug, not the cord;
- Do not put heavy things on the power cord or bend it too much;
- Do not take out the backup battery without the guide of qualified service personnel;
- If the unit is not working for any reason, do not attempt to repair the instrument. Only qualified service personnel been permitted to service the instrument;
- Place the Instrument and the power supply in a properly ventilated place. Do not place the Instrument near high temperature objects, under direct sunlight, near source of water, near fire or near inflammable and explosive materials;
- Do not place any articles over the instrument;
- Place the Instrument in a dry place and do not expose to moisture;
- Place the Instrument away from other electronic devices like TV and Radio to avoid interference;
- For a better reception, do not place the Instrument in a building with iron or metal roof. Hospitals or health care facilities may be using equipment sensitive to Radio Frequencies. Please ensure that your phone is turned off while in the vicinity of such facilities;
- Do not use the unit in designated "No Service" area;
- This phone use UIM card, don't use this card anywhere else;
- The software keeping upgrading, so the operation menu maybe little different from the manual;

Main Features


- Suitable for GSM900/1800MHz network; (Optional: GSM850/900/1800/1900Mhz)
- Redial function;
- Phonebook function;
- Hands-free function;
- Hands-free and ringer volume adjustable;
- Different ring tones and alarm ringers;
- Short message;
- MP3 and FM radio function;
- Backlight LCD with date, time, signal strength and battery volume status icons;
- Can save, check, delete and call back incoming, outgoing and missed calls;

Technical Information

- Standby time: 48 hours;
- Sensitivity: -105dB;
- Working temperature: -10 degree - +45 degree;
- Working humidity: 10% - 95%;
- Atmosphere pressure: 86 - 106Kpa;
- Frequency: GSM 850/900/1800/1900MHz;
- Battery: rechargeable;
- Conversation time: 2 hours;
- Working voltage: AC220V, 50Hz, DC 5V 1000mA

Notes: Standby & conversation time subject to local network signal strength;

Phone Description



1. Handset;
2. DC plug socket: connect with AC power;
3. LCD display;
4. OK key: confirm your selection in main menu operation;
5. ▲: Press this key to increase the volume during conversation; press this key to turn to up page during main menu operating;
In standby state press this key to enter Alarm setting state;
6. Menu: press key to check the menu during standby state;
7. ◀: Press this key to edit SMS in standby state, press to turn left during SMS input state;
8. ▼: Press this key to decrease the volume during conversation; press this key to turn to down page during main menu operating;
9. Number keys;
10. ON/OFF: in standby state, press and hold this key for 3 seconds to turn on the phone, press and hold this key for another 3 seconds to turn off the phone,
11. Return: in menu operation state, press this key to exit operation; When new call come, press this key one time for MUTE state, press this key two times to reject the incoming calling;
12. ▶: In standby state, press this key to review incoming, outgoing and missed call records; press this key to turn right during SMS input state;
13. Audio: In standby state, press this key to select ring tones;
14. Delete: delete what you input during input state;
15. Redial: in standby state, press this key to dial last dialed number out;
16.  : press this key to dial the number out without any waiting; in standby state, press this key to review outgoing numbers list;
17. Hands-free key

Installation

- 5.1 Open battery door, put the SIM card into card holder which metal face toward to the PCB board of the phone, make SIM card connect well with the card holder;
- 5.2 Install the battery into battery door and install battery cover;
- 5.3 Connect the adapter with the phone and the power;
- 5.4 Press and hold ON/OFF key for 3 seconds to turn on the phone;

Basic Operation

6.2 Make calling

- 6.2.1 Pick up handset and hear dialing tone, input desired number and press “” key the number will be dialed out without any delay, or it'll dial out after 5 seconds;
- 6.2.2 Press “Redial” key to dial last dialed number out;
- 6.2.3 When find desired number in the call list, press “” key can dial this number out directly. During conversation, LCD display conversation time, return the handset to the base or press Hands-free key after conversation;

6.3 Pick up calling

When new call come, phone ring and LCD display incoming number, pick up handset or press Hands-free key to proceed conversation, return handset to base or press Hands-free key to finish the conversation;

6.4 Redial Function

Pick up handset or in standby state press “Redial” key, the last dialed number will be dialed out;

6.5 Hands-free

Press Hands-free to have conversation in Hands-free state, press Hands-free key again to finish Hands-free state;

6.6 Adjust conversation volume

Press ▼ key to decrease conversation volume during conversation, press ▲ key to increase conversation volume, total 15 levels. When use handset have conversation can adjust handset volume, when use Hands-free have conversation can adjust Hands-free volume;

Menu Operation

7.2 Short Message

In standby state, press “OK” key two times to enter short message state.

Settings: Message center: please check with your network operator to get the message center number;

Message validity period: can make different selections;

Status report: you can select it on or off;

Save sent messages: you can select save or not save;

Preferred storage: you can select to save the message in phone or SIM card;

7.3 Call logs

You can press ▲ or ▼ key to select Dialed calls; Received calls; Missed calls; Delete call;

7.4 Contacts

You can press ▲ or ▼ key to select contact list saved in SIM card or phone;

7.5. Settings

You can press ▲ or ▼ key to select Call settings (you can press ▲ or ▼ key to select Network selection; Call divert; Call waiting; Call barring; others);

Phone settings (you can press ▲ or ▼ key to select Language settings; Shortcut settings; Restore factory settings);

Display (you can press ▲ or ▼ key to select Adjust contrast; Backlight);

Security (you can press ▲ or ▼ key to select different PIN code);

Profiles (you can press ▲ or ▼ key to select Normal or Silent);

7.6. Clock

You can press ▲ or ▼ key to select Set time; Set date; Time format; Date format; Alarm; When you select Alarm, you can press ▲ or ▼ key to select Ringtone or Ringtone1; When you finish the setting, you can ▲ or ▼ key to select Repeat mode once, Daily and Working days;

7.7. FM radio

You can press ▲ or ▼ key to select different frequency, or press ▲ or ▼ key to adjust volume;

Troubleshooting

LCD no display or no backlight:

Reason: no power;

Resolution: use original adapter connect with power;

Couldn't dial out:

Reason:

1. Network signal problem;
2. Signal interference;

Resolution:

1. Wait some time to redial;
2. Turn off the phone and re-start it;

Have backlight but no display:

Reason: battery use up;

Resolution: connect with power to charge battery;

Couldn't find SIM card:

1. Battery use up;
2. SIM card connector isn't good;

Resolution:

1. Connect with power to charge battery;
2. Adjust the card holder so that card can connect card holder well;